



Wi-Fi Smart Bulb



Quick Start Guide

## GETTING STARTED

1. Make sure that your smart phone is connected to 2.4Ghz WiFi network at all times when performing add device.
2. Have your 2.4Ghz WiFi network password with you.
3. Smart phone is running on Android 4.0 / iOS 8.0 or higher.
4. Your router encryption is set to WEP / WPA / WPA2 and MAC filtering is disabled.

## DOWNLOAD APP


Scan QR code below to download app



Android 4.0 / iOS 8.0 and above

# ACCOUNT REGISTRATION / LOGIN

1. For first time user, create an account and follow on-screen instructions to get verification code to complete your new account registration.



## ADD DEVICE

1. Install Eva Smart Bulb onto an E27 base and turn on the power.
2. There are 3 modes of adding Eva Smart Bulb into the app.
  - EZ Mode (Default / Commonly used)
  - AP Mode
  - Bluetooth (Auto search when your phone's Bluetooth is on)

## EZ MODE SETUP (DEFAULT)

1. Ensure the bulb is blinking fast (twice per second). If it is blinking slowly (once every 3 seconds), then turn off and on the bulb consecutively for 3 times to reset / switch it to EZ Mode (fast blink).

To reset or switch  
setup mode



OFF - ON x3



**Light indicator**

Fast blink:  
EZ Mode setup (default)


Slow blink:  
AP Mode setup


2. Ensure your phone is connected to 2.4GHz WiFi network.
3. Tap on the **+** icon at the top right corner of the app.
4. If your phone's Bluetooth is on, you will automatically get a new device prompt. Tap on it and proceed to add the bulb.
5. If not, then choose device type "**Lighting - Light Source (BLE + Wi-Fi)**" and add manually.
6. Ensure your phone is connected to 2.4GHz WiFi network.
7. Key in your 2.4GHz WiFi password manually when prompted, do not copy and paste the password.
8. Follow on-screen instructions to proceed further.
9. Once Eva Smart Bulb has been successfully setup, the light will stop flashing.



## AP MODE SETUP


AP mode setup is recommended for Mesh WiFi home network, or WiFi network that uses the same SSID for both 2.4GHz and 5GHz network.


1. Switch Eva Smart Bulb to AP Mode setup.
2. Make sure the bulb is blinking slowly (once every 3 seconds). If not, turn off and on the switch for 3 consecutive times. (off-on-off-on-off-on) to switch setup to AP Mode (slow blink).
3. Tap on the  icon at the top right corner of the app.
4. Select device type "**Lighting - Light Source (BLE + Wi-Fi)**"
5. At the top right corner, Switch app configuration to "AP Mode"
6. Ensure your phone is connected to 2.4GHz WiFi network.



7. Hit next and follow on-screen instructions to proceed with the setup.

## CONNECTING TO 3RD PARTY VOICE SERVICE

1. From the Eva Smart Bulb panel, tap on the  icon at the upper right corner to open up the device information panel.
2. At "Third-party Control" section, select the desired voice control service to link. (Tmall Genie only works on Tuya Smart app)
3. Follow the on-screen instruction to proceed further.



Swipe left for more services.


Enable to get notification when Eva Smart Bulb goes offline.



Share Eva Smart Bulb with other users.

Create a group with other Eva Smart Bulb to control simultaneously.

Add a shortcut to this Smart Bulb on your phone's home screen.

# DEVICE SHARING

1. From the Eva Smart Bulb main panel, select the  (pencil) icon to open up the "device information panel".
2. Select "Share Device" from the selection.
3. Select "Add Sharing" button at the bottom.
4. Follow on screen instructions to proceed to add member.



Share to app account users.

Create invite link for number of users.

Share link via other app.

Copy invite link.

Share invite link via email.

Share invite link via SMS.



# HOME SHARING

1. From the app main panel, select "Me" on the bottom right. Then select "Home Management" from the selection.
2. Choose a home that you would like to share.  
**NOTE: Home must be set up first.**
3. Select "Add Member", and choose your desired sharing method.

Choose a home to share if you have multiple home created:

Home Management

Home Settings

Home Name: Apartment >

Room Management: 4 Rooms >

Home Location: Potting 13, Jalan Tim 2/8 >

Home Member:

- User 1: Administrator >
- User 2: Administrator >
- User 3: Home Owner >

Add Member

Share

App account, Message, Email, Copy, More

Cancel

Current added members.

Add member.

Invite app account user.

Share invite link via SMS.

Share link via other app.

Copy invite link.

Share invite link via email.

# HOME AUTOMATION FUNCTION

Eva Smart Bulb can be automated alongside with other smart devices that bears the marking "Powered by Tuya" / devices that works with "Smart Life" or "Tuya Smart" app.

- Devices are required to be added into the same app to work.



Powered by Tuya label



Tuya Smart app



Smart Life app

There are mainly 2 types of automation:


## 1. Tap-to-Run


- Used for creating a "scene" or a shortcut button.
- A series of continuous action with the tap of a button.
- Can be used to execute actions from different devices.

## 2. Automation (Smart)

- Actions that run automatically when a pre-defined condition is met.
- Such as timer / schedule, location changes, device status changes, weather changes.

# ADDING AUTOMATION

1. At the app main panel, select “Smart” at the bottom of the panel.
2. Select the  icon on the upper right corner to add new automation.
3. Select an automation type and follow on-screen selections to add new automation.



Tap-to-Run automation.

Smart automation.

## FAQ AND TROUBLESHOOTING

- 1. Why can't I turn on/off Eva Smart Bulb? / It says offline.**
  - Make sure your home WiFi network is stable.
  - Make sure the power is on.
  
- 2. What should I do when adding device process has failed?**
  - Check if Eva Smart Bulb is turned on.
  - Check if your smart phone is connected to 2.4GHz WiFi network.
  - Make sure your WiFi password entered in the app during adding device procedure is correct.
  - Key in your WiFi password instead of copy and paste.
  - Make sure Eva Smart Bulb is in ready state for app configuration.
    - Light fast blink (twice per second) - EZ Mode
    - Light slow blink (once every 3 seconds) - AP Mode

If not, turn power off and on for 3 consecutive times (off-on-off-on-off-on)

  - Check your internet connection, make sure router and internet is working properly.

- If you're using Mesh WiFi, we recommend you adding Eva Smart Bulb using AP Mode (slow blink).
- Make sure router's broadcasting mode is enabled.
- Make sure router's encryption mode is set to WPA2-PSK and authorization mode is AES, or set both to Auto.
- Check if WiFi signal is strong enough at the Eva Smart Bulb location. If weak, relocate Eva Smart Bulb to within router's WiFi range.
- Check whether your router has reached maximum number of devices (usually max 30 devices). Disconnect some device WiFi connection and try again.
- Check if router's wireless MAC filtering function is enabled. Remove the device from filter list and make sure the router is not prohibiting Eva Smart Plug from connecting.

### 3. **Can I control Eva Smart Bulb using my mobile 3G/4G network?**

- After first time setup / added into app, you can remotely access and control Eva Smart Bulb using 3G/4G mobile network from your phone.



View demo videos.



View in-depth tutorials.



For more info, please visit:  
[www.evasmart.co](http://www.evasmart.co)